

ELECTRICITY

CHAPTER NO.12

SUB: PHYSICS

CHANGING YOUR TOMORROW

Website: www.odmegroup.org

Email: info@odmps.org

Toll Free: **1800 120 2316**

Sishu Vihar, Infocity Road, Patia, Bhubaneswar-751024



LEARNING OUTCOMES

- •Students will be able to :
- Define Ohm's law
- Experimentally verify Ohm's law.
- Solve numerical problems on Ohm's law.
- Define resistance.
- Define resistivity.
- Solve numerical problems on resistance and

CHANGING YOUR TOMORROW

Website: www.odmegroup.org Toll Free: 1800 120 2316

Email: info@odmps.org Sishu Vihar, Infocity Road, Patia, Bhubaneswar- 751024



POINTS TO BE COVERED

Ohm's Law

Solve numerical problems on Ohm's Law.

Resistance.

Resistivity.

CHANGING YOUR TOMORROW

Website: www.odmegroup.org

Email: info@odmps.org

Toll Free: **1800 120 2316**

Sishu Vihar, Infocity Road, Patia, Bhubaneswar- 751024

OHMS LAW.

The electric current flowing through a conductor is directly proportional to the potential difference applied across its ends providing the physical conditions such as temperature remains unchanged.

 $V \alpha I$

V = IR. Where R is a constant called resistance.

Ohmic conductors

The conductors which obey ohms law are known as Ohmic conductor.

Non ohmic conductors

The conductors which do not obey Ohms law are known as non ohmic conductors. https://youtu.be/ldNPl67x-E8

RESISTANCE

https://youtu.be/4UAe_sXFH4A

FACTORS ON WHICH THE RESISTANCE OF A CONDUCTOR DEPENDS

The resistance of a conductor depends upon its:-

- i) Length
- ii) Area of cross section
- iii) Material of the conductor.

Resistance is directly proportional to the length of the conductor and inversely proportional to the area of cross section of the conductor.

$$R \alpha I$$
 $R \alpha I / A$
or $R \alpha I$
 A
or $R = \rho I$

Where ρ (rho) is a constant of proportionality called Resistivity of the material of the conductor.

The SI unit of resistivity is ohm meter (Ω m).

NUMERICALS

Q1. The pd between the terminals of an electric heater is 75 volt when it draws a current of 5A from the source. What current will the heater draw, if the pd is increased to 150 V.

```
Answer: V = 75 \text{ V}.

I = 5A \quad R = V/I = 75 / 5 = 15\Omega

R = 15\Omega. V2 = 150 \text{ V}. I2 = V2/R = 150 / 15 = 10A.
```

Q2. A wire of given material having length I and area of cross-section A has a resistance of 10 Ω . What would be the resistance of another wire of the same material having length I/4 and area of cross-section 2.5 A?

```
Answer: Length = I

Area of cross section = A.

R1 = p I/A = 10\Omega.

P = 10 \text{ A/I}.

For second wire length = I/4.

A = 2.5 \text{ A}.

R2 = p I/4 ÷2.5 \text{A} = 10 \text{ A/I} \times \text{I/} 4 \times 2.5 \text{ A} = 10 \text{ A/I} \times \text{I/} 4 \times 2.5 \text{ A} = 10 \text{ A/I} \times \text{I/} 4 \times 2.5 \text{ A} = 10 \text{ A/I} \times \text{I/} 4 \times 2.5 \text{ A} = 10 \text{ A/I} \times \text{I/} 4 \times 2.5 \text{ A} = 10 \text{ A/I} \times \text{I/} 4 \times 2.5 \text{ A} = 10 \text{ A/I} \times \text{I/} 4 \times 2.5 \text{ A} = 10 \text{ A/I} \times \text{I/} 4 \times 2.5 \text{ A} = 10 \text{ A/I} \times \text{I/} 4 \times 2.5 \text{ A} = 10 \text{ A/I} \times \text{I/} 4 \times 2.5 \text{ A} = 10 \text{ A/I} \times \text{I/} 4 \times 2.5 \text{ A} = 10 \text{ A/I} \times \text{I/} 4 \times 2.5 \text{ A} = 10 \text{ A/I} \times \text{I/} 4 \times 2.5 \text{ A} = 10 \text{ A/I} \times \text{I/} 4 \times 2.5 \text{ A} = 10 \text{ A/I} \times \text{I/} 4 \times 2.5 \text{ A} = 10 \text{ A/I} \times \text{I/} 4 \times 2.5 \text{ A} = 10 \text{ A/I} \times \text{I/} 4 \times 2.5 \text{ A} = 10 \text{ A/I} \times \text{I/} 4 \times 2.5 \text{ A} = 10 \text{ A/I} \times \text{I/} 4 \times 2.5 \text{ A} = 10 \text{ A/I} \times \text{I/} 4 \times 2.5 \text{ A} = 10 \text{ A/I} \times \text{I/} 4 \times 2.5 \text{ A} = 10 \text{ A/I} \times \text{I/} 4 \times 2.5 \text{ A} = 10 \text{ A/I} \times \text{I/} 4 \times 2.5 \text{ A} = 10 \text{ A/I} \times \text{I/} 4 \times 2.5 \text{ A} = 10 \text{ A/I} \times \text{I/} 4 \times 2.5 \text{ A} = 10 \text{ A/I} \times \text{I/} 4 \times 2.5 \text{ A} = 10 \text{ A/I} \times \text{I/} 4 \times 2.5 \text{ A} = 10 \text{ A/I} \times \text{I/} 4 \times 2.5 \text{ A} = 10 \text{ A/I} \times \text{I/} 4 \times 2.5 \text{ A} = 10 \text{ A/I} \times \text{I/} 4 \times 2.5 \text{ A} = 10 \text{ A/I} \times \text{I/} 4 \times 2.5 \text{ A} = 10 \text{ A/I} \times \text{I/} 4 \times 2.5 \text{ A} = 10 \text{ A/I} \times \text{I/} 4 \times 2.5 \text{ A} = 10 \text{ A/I} \times \text{I/} 4 \times 2.5 \text{ A} = 10 \text{ A/I} \times \text{I/} 4 \times 2.5 \text{ A} = 10 \text{ A/I} \times \text{I/} 4 \times 2.5 \text{ A} = 10 \text{ A/I} \times \text{I/} 4 \times 2.5 \text{ A} = 10 \text{ A/I} \times \text{I/} 4 \times 2.5 \text{ A} = 10 \text{ A/I} \times \text{I/} 4 \times 2.5 \text{ A} = 10 \text{ A/I} \times \text{I/} 4 \times 2.5 \text{ A} = 10 \text{ A/I} \times 10 \times 4 \times 2.5 \text{ A} = 10 \text{ A/I} \times 10 \times 4 \times 2.5 \text{ A} = 10 \text{ A/I} \times 10 \times 2.5 \text{ A}
```

SERIES COMBINATION

https://youtu.be/pd3RkGs1Tsg

THANKING YOU ODM EDUCATIONAL GROUP

